

12-15V AC, 300W Transformer

A 300W transformer, in a stainless-steel case. Enough power to run most landscape light systems. For bigger properties, run 2 units.



FEATURES

- Stainless steel case
- 300W output, 110V input
- 1 common terminal, with 12V, 13V, 14V, 15V terminals
- 6.1" by 5.3" by 11.6" dimensions
- Quick mount bracket
- Sealed removable lockable hinged door
- Pre-scored knockout sides and bottom panel
- Tool-less removable bottom panel
- Fully encapsulated Toroid Core
- 304L stainless steel enclosure
- 15 years warranty



| SPECIFICATIONS | | |
|---------------------|---------------------------------|--|
| Product Code | ACC-TR-300W | |
| Electrical | Input Voltage | 120V |
| | Output Voltage | 12V, 13V, 14V, 15V AC |
| | Power | 300W |
| | Max Output Current | 8.5A |
| | Primary Protection | 25 AMP breaker |
| Specs | Colour Temperature | Cool White 98 lumens @ 5500K; Warm White 95 lumens @ 2700K |
| | Life Span | 50,000 Hours |
| Design | Dimensions (Inches) | 11.6 x 6.1" |
| | Dimensions (Millimeters) | 295 x 155mm |
| | Finish | Black |
| | Material | Composite |
| | Operating Temperature | -20 to 40°C |
| | Mounting | On Wall |
| | IP Rating | IP65 |
| Warranty | 15 years | |
| Approvals | cETLus | |

DIAGRAM



ACCESSORIES



ACC-DT
Digital Timer



ACC-PC
Photocell



ACC-WIFI
WI-FI Controller



ACC-12G-2C-BUR
Landscape burial wire, 12G, 2C - 500ft spool

ACC-12G-2C-BUR-XX
Landscape burial wire, 12G, 2C - custom cuts